

GROUP D



208/240/277/380/480 PRIMARY VOLTS — 24 SECONDARY VOLTS — 1Ø, 50/60 Hz

CATALOG NO.	VA RATING	OUTPUT AMPS	APPROX. DIMENSIONS Inches (Cm.)						APPROX. SHIP WEIGHT Lbs. (Kg.)	PRIMARY FUSE BLOCK Part No.	SECONDARY FUSE KIT ① Part No.	SECONDARY FUSE SIZE 24 VOLTS
			A	B	C	D	E	F				
TA-2-81321	50	2.08	4.08 (10.4)	3.75 (9.5)	3.21 (8.2)	3.13 (8.0)	2.19 (5.6)	.22 x .50 (0.6 x 1.3)	4 (1.8)	PL-112701	PL-112602	3 ² / ₁₀ amp
TA-2-81322	75	3.13	4.31 (10.9)	3.75 (9.5)	3.21 (8.2)	3.13 (8.0)	2.31 (5.9)	.22 x .50 (0.6 x 1.3)	5 (2.3)	PL-112701	PL-112602	5 amps
TA-2-81323	100	4.17	4.52 (11.5)	3.75 (9.5)	3.21 (8.2)	3.13 (8.0)	2.63 (6.7)	.22 x .50 (0.6 x 1.3)	5 (2.3)	PL-112701	PL-112602	6 ¹ / ₄ amps
TA-2-81324	150	6.25	4.75 (12.1)	4.50 (11.4)	3.84 (9.8)	3.75 (9.5)	3.05 (7.7)	.22 x .50 (0.6 x 1.3)	9 (4.1)	PL-112702	PL-112601	10 amps
TA-2-81325	250	10.42	5.24 (13.3)	4.88 (12.4)	4.15 (10.5)	4.06 (10.3)	3.25 (8.3)	.22 x .50 (0.6 x 1.3)	11 (5.0)	PL-112703	PL-112601	15 amps
TA-2-81326	350	14.58	6.02 (15.3)	5.25 (13.3)	4.47 (11.4)	4.38 (11.1)	4.00 (10.2)	.31 x .50 (0.8 x 1.3)	18 (8.2)	PL-112704	PL-112601	20 amps
TA-2-81327	500	20.83	6.51 (16.5)	5.25 (13.3)	4.47 (11.4)	4.38 (11.1)	4.19 (10.6)	.31 x .50 (0.8 x 1.3)	19 (8.6)	PL-112704	PL-112601	30 amps
TA-2-81328	750	31.25	7.08 (18.0)	6.75 (17.1)	5.72 (14.5)	5.75 (14.6)	3.81 (9.7)	.31 x .50 (0.8 x 1.3)	26 (11.8)	PL-112705	—	—
TA-2-81329	1000	41.67	8.10 (20.6)	6.75 (17.1)	5.72 (14.5)	5.75 (14.6)	4.63 (11.8)	.31 x .50 (0.8 x 1.3)	33 (15.0)	PL-112705	—	—

GROUP E

208/277/380 PRIMARY VOLTS — 115/95 SECONDARY VOLTS — 1Ø, 50/60 Hz

CATALOG NO.	VA RATING	OUTPUT AMPS	APPROX. DIMENSIONS Inches (Cm.)						APPROX. SHIP WEIGHT Lbs. (Kg.)	PRIMARY FUSE BLOCK Part No.	SECONDARY FUSE KIT ① Part No.	SECONDARY FUSE SIZE 115 VOLTS
			A	B	C	D	E	F				
TA-2-81301	50	0.43	4.35 (11.0)	3.00 (7.6)	2.59 (6.6)	2.50 (6.4)	2.61 (6.6)	.22 x .50 (0.6 x 1.3)	4 (1.8)	PL-112700	PL-112600	⁶ / ₁₀ amp
TA-2-81302	75	0.65	4.74 (12.0)	3.00 (7.6)	2.59 (6.6)	2.50 (6.4)	2.81 (7.1)	.22 x .50 (0.6 x 1.3)	4 (1.8)	PL-112700	PL-112600	1 amp
TA-2-81303	100	0.87	4.45 (11.3)	3.75 (9.5)	3.21 (8.2)	3.13 (8.0)	2.44 (6.2)	.22 x .50 (0.6 x 1.3)	5 (2.3)	PL-112701	PL-112600	1 ¹ / ₄ amps
TA-2-81304	150	1.30	5.00 (12.7)	3.75 (9.5)	3.21 (8.2)	3.13 (8.0)	3.06 (7.8)	.22 x .50 (0.6 x 1.3)	5 (2.3)	PL-112701	PL-112600	2 amps
TA-2-81305	250	2.17	5.68 (14.4)	4.50 (11.4)	3.84 (9.8)	3.75 (9.5)	4.06 (10.3)	.22 x .50 (0.6 x 1.3)	13 (5.9)	PL-112702	PL-112601	3 ¹ / ₂ amps
TA-2-81306	350	3.04	6.30 (16.0)	4.88 (12.4)	4.15 (10.5)	4.06 (10.3)	4.75 (12.1)	.22 x .50 (0.6 x 1.3)	18 (8.2)	PL-112703	PL-112601	5 amps
TA-2-81307	500	4.35	6.22 (15.8)	5.25 (13.3)	4.47 (11.4)	4.38 (11.1)	4.56 (11.6)	.31 x .50 (0.8 x 1.3)	20 (9.1)	PL-112704	PL-112601	7 amps
TA-2-81308	750	6.52	6.82 (17.3)	6.75 (17.1)	5.72 (14.5)	5.75 (14.6)	3.69 (9.4)	.31 x .50 (0.8 x 1.3)	24 (10.9)	PL-112705	PL-112601	10 amps
TA-2-81309	1000	8.70	7.96 (20.2)	6.75 (17.1)	5.72 (14.5)	5.75 (14.6)	4.44 (11.3)	.31 x .50 (0.8 x 1.3)	31 (14.1)	PL-112705	PL-112601	12 amps

① Secondary Fuse Kit PL-112603 may be substituted for PL-112600 thru PL-112602 when Primary Fuse Kit is used. See page 75.