

Non-Reversing

Instakits™ (1)



LE1D●●3A62

Maximum HP							NEMA	NEMA	NEMA
1 Phase 3 Phase							Type 1	Type 12	Type 4
120V	240V	208V	230V	460V	575V	Assembly	Catalogue	Catalogue	Catalogue
Hp	Hp	Hp	Hp	Hp	Hp	(2) (3)	Number (4)	Price	Number (4)
0.3	1	2	2	5	7.5	Factory	LE1D093A62O●	\$552.	LE1D093A72O●
						Customer	LE1D093A62OG70	408.	LE1D093A72OG70
0.5	2	3	3	7.5	10	Factory	LE1D123A62O●	670.	LE1D123A72O●
						Customer	LE1D123A62OG70	526.	LE1D123A72OG70
1	3	5	5	10	15	Factory	LE1D183A62O●	738.	LE1D183A72O●
						Customer	LE1D183A62OG70	578.	LE1D183A72OG70
2	3	7.5	7.5	15	20	Factory	LE1D253A62O●	794.	LE1D253A72O●
						Customer	LE1D253A62OG70	634.	LE1D253A72OG70
2	5	10	10	20	25	Factory	LE1D323A62O●	1028.	LE1D323A72O●
						Customer	LE1D323A62OG70	800.	LE1D323A72OG70
3	5	10	10	30	30	Factory	LE1D403A62O●	1192.	LE1D403A72O●
						Customer	LE1D403A62OG70	964.	LE1D403A72OG70
3	7.5	15	15	40	40	Factory	LE1D503A62O●	1358.	LE1D503A72O●
						Customer	LE1D503A62OG70	1018.	LE1D503A72OG70
5	10	20	20	40	50	Factory	LE1D653A62O●	1558.	LE1D653A72O●
						Customer	LE1D653A62OG70	1218.	LE1D653A72OG70
7.5	15	25	30	60	60	Factory	LE1D803A62O●	1710.	LE1D803A72O●
						Customer	LE1D803A62OG70	1370.	LE1D803A72OG70
-	-	30	40	75	75	Factory	LE1D113A62O●	2232.	LE1D113A72O●
						Customer	-	-	-
-	-	40	50	100	100	Factory	LE1D153A62O●	2272.	LE1D153A72O●
						Customer	-	-	-
-	-	50	60	125	125	Factory	LE1F183A62O●	3512.	LE1F183A72O●
						Customer	-	-	-
-	-	60	75	150	150	Factory	LE1F263A62O●	4952.	LE1F263A72O●
						Customer	-	-	-
-	-	75	100	200	200	Factory	LE1F333A62O●	8268.	LE1F333A72O●
						Customer	-	-	-
-	-	100	125	250	250	Factory	LE1F403A62O●	11584.	LE1F403A72O●
						Customer	-	-	-
-	-	150	200	400	400	Factory	LE1F503A62O●	32512.	LE1F503A72O●
						Customer	-	-	-
-	-	-	300	600	600	Factory	LE1F633A61O●	43184.	LE1F633A71O●
						Customer	-	-	-

(1) Instakits™ design available in NEMA Type 1 and Type 12 enclosures only.

(2) Factory assembled:

a) Replace (●) with corresponding coil voltage code in the table below.

Voltage (volts)	24V	120V	208V	240V	480V	600V
Code	B7	G7	L7	M7	T7	X7

b) Replace (□) with corresponding O/L relay suffix number listed on page 1. (Price included in starter price.)

(3) Customer Assembled:

a) For coil voltage other than 120 volts, replace suffix letter G7 by corresponding letter on above coil voltage table.

b) Select exact O/L relay part number on page 24 / 25 and add price to starter price.

(4) To obtain a single phase non-reversing starter, change prefix LE1 to LES. (eg. LE1D093A62OG70 becomes LESD093A62OG70). Price remains unchanged. Not applicable to LE1F● devices.

How to Order:

To Order Specify:	Example			
● Catalogue Number	Catalogue	Coil	Overload	
● Coil Voltage Code	Number	Voltage	Relay	Factory
● Overload Relay Suffix		Code	Suffix	Mod's
● Factory Modifications (alphabetical order)	LE1D093A62O	G7	112	

Catalogue numbers	pages 2 to 11
Overload relays	pages 24 to 25
Factory Modifications	pages 12 to 17
Dimensions	pages 18 to 21
Wiring Diagrams	pages 22 to 23