


Data sheet | Item number: 2001-402

TOPJOB®S jumper; for 2001 series; insulated; 2-way; light-gray



 Picture differs from the item.

RoHS 
Compliant

 BOMcheck.net

Color: 

Data
Electrical data

Subject to changes. Please also observe the further product documentation!



IEC Approvals

Rated voltage (III / 3)	800 V
Rated current	18 A

Ex information

Rated current (Ex e II)	16 A
-------------------------	------

Physical data

Width	7 mm / 0.276 inch
Height	4.1 mm / 0.161 inch
Depth	19 mm / 0.748 inch

Material data

Color	light gray
Fire load	0.006 MJ
Weight	0.7 g

Commercial data

Product Group	22 (TOPJOB S)
Packaging type	bag
Country of origin	DE
GTIN	4055143698412
Customs tariff number	8536698000

Downloads

Documentation

Bid Text

2001-402 X81 - Datei	Feb 19, 2019	xml 2.6 kB
-------------------------	--------------	---------------

2001-402 doc - Datei	Apr 27, 2017	doc 24.1 kB
-------------------------	--------------	----------------

Additional Information

Technical explanations	Apr 3, 2019	pdf
------------------------	-------------	-----

Subject to changes. Please also observe the further product documentation!



CAD files

CAD data

2D/3D Models 2001-402

CAE data

EPLAN Data Portal 2001-402

WSCAD Universe 2001-402

ZUKEN Portal 2001-402

Environmental Product Compliance

Compliance Search



Environmental Product Compliance 2001-402

Jumper; 2-way; insulated; light gray

Installation Notes

Commoning

Subject to changes. Please also observe the further product documentation!



The push-in type jumper bar system is based on the common plug and socket principle. Each terminal block is spring-loaded with a double socket and a resilient CrNi steel spring. The jumper contact material is pure electrolytic copper, which allows for an extremely small design capable of carrying the full-rated current of the terminal block. Ground terminal blocks can also be commoned using the same jumper system. Custom jumpers are created by breaking and removing jumper contacts (2000, 2001, 2002, 2004 Series).

Removing a push-in type jumper bar:

Insert the operating tool between the jumper and partition wall of the dual jumper slots, then lift up the jumper.

Place the operating tool in the center of jumpers for up to five contacts (see above), or alternately on both sides for jumpers with more than five contacts.

Commoning



Push-in type jumper bars

Custom push-in type jumper bars are created by breaking off jumper contacts.

500 V

300 V

Push-in type jumper bars


Marking with a felt-tip pen.

Commoning

Subject to changes. Please also observe the further product documentation!



Stepping down via push-in type jumper bar.




Stepping down via push-in type jumper bar:

Commoning via closed terminal side with end plate allows jumpering over two cross-section sizes, e.g., from 16 mm² (6 AWG) to 6 mm² (10 AWG) or from 6 mm² (10 AWG) to 2.5 mm² (14 AWG) (see illustration above).



Stepping down via push-in type jumper bar:

Commoning via open terminal side with end plate allows jumpering over two cross-section sizes for 16 mm² (6 AWG) and 10 mm² (8 AWG) and one cross-section size for 6/4/2.5 mm² (10/12/14 AWG). An example: from 16 mm² (6 AWG) to 6 mm² (10 AWG) (see illustration above) or from 10 mm² (8 AWG) to 4 mm² (12 AWG).



Note:

The total current of the outgoing circuits must not exceed the nominal current of the step-down jumper/push-in type jumper bar.

Product family

TOPJOB® S

TOPJOB® S: In various industrial applications and modern building installations, WAGO's wide and versatile range of rail-mount terminal blocks provides more than just reliable electrical connections.

[Show all products from the family](#)

Subject to changes. Please also observe the further product documentation!